

Features:

- True diversity 500MHz UHF wireless belt-pack transmitter
- Over 1000 Select-able UHF channels
- Operates on two inexpensive AA batteries
- Infrared auto sync function
- Integrated ON/OFF/MUTE switch
- LCD display with ON/ MUTE/ FREQ display
- Battery level indicator
- Works with condenser microphones
- Miniature 3 pin XLR connector

The WBP-10 functions with the following wireless systems:

- WMX-UHF-H
- WMX-UHF-HS
- WMX-2UHF-H
- WMX-2UHF-HB
- WM1-UHF
- WM1-UHF-HS

The WBP-10 connects to the following microphones:

- HSM-09
- HSM-04
- LAV-09
- CMIC-EAR
- CMIC-HS

Specifications:

Belt-pack Transmitter:

- Carrier wave freq range - UHF 516-541MHz
- Operating frequency – UHF 516-541MHz
- Frequency selection - Infrared
- Oscillation Mode – Phase-lock loop controlled
- Carrier wave stability - 10PPM
- Frequency Response – 40Hz- 18kHz
- Sensitivity - (-74dB +/- 3dB)
- ON/OFF/MUTE switch – Yes
- Power – 10mW or 20mW switchable
- Spurious Emission <40dB (with carrier)
- Display – LED
- Current drain <130mA
- Battery voltage 1.5V x 2 AA batteries
- Battery life- 6-8 hours approx

Dimensions: (W x D x H)

- W= 2.5"
- D = 1.0"
- H= 3.25" (without antenna)
- Shipping Weight **0.5 lbs** (0.22kg)

